

# IP-HFLK10(20)B31C

SFP 10Gb/s 1310nm Single-mode 10(20) km DDM

## PRODUCT FEATURES

- Up to 11.3Gbps Data Links
- 1310nm DFB laser transmitter and PIN/TIA receiver
- Up to 10(20) km on 9/125µm SMF
- Hot-pluggable SFP footprint
- Duplex LC/UPC type pluggable optical interface
- Low power dissipation
- Metal enclosure, for lower EMI
- RoHS compliant and lead-free
- Support Digital Diagnostic Monitor interface
- Single +3.3V power supply
- Compliant with SFF-8472
- Case operating temperature

Commercial: 0°C to +70°C



## APPLICATIONS

- 10G Ethernet 10GBASE-LR/-LW
- 1200-SM-LL-L 10G Fiber Channel

## Compliance

- SFF-8472 SFP+ MSA.
- SFP+ SFF-8431 and SFF-8432.
- Fiber Channel 1200-SM-LL-L
- IEEE802.3ae
- RoHS

## PRODUCT DESCRIPTION

IP-HFLK10(20)B31C SFP+ transceivers are compatible with the Small Form Factor Pluggable Multi-Sourcing Agreement (MSA). The transceiver consists of five sections: the LD driver, the limiting amplifier, the digital diagnostic monitor, the 1310nm DFB laser and the PIN/TIA. The module data link up to 20km in 9/125umSingle-mode fiber.

This transceiver meets the SFP+ industry standard package utilizing an integral LC-Duplex optical interface connector. An enhanced Digital Diagnostic Monitoring Interface compliant with SFF-8472 has been incorporated into the transceiver. It allows real time access to the transceiver operating parameters such as transceiver temperature, laser bias current, transmitted optical power, received optical power and transceiver supply voltage by reading a built-in memory with I<sup>2</sup>C interface.

The optical output can be disabled by a LVTTTL logic high-level input of Tx Disable, and the system also can disable the module via I<sup>2</sup>C. Tx Fault is provided to indicate that degradation of the laser. Loss of signal (LOS) output is provided to indicate the loss of an input optical signal of receiver or the link status with partner. The system can also get the LOS (or Link)/Disable/Fault information via I<sup>2</sup>C register access.

## Contact Information

Inphilight Technology (WuHan) Co., Ltd

Inphi (WuHan) Opto tech Co., Ltd

ADD: Building 5, Zone E, Guangguxin Center, No.52, Road liufang, Jiangxia district, Wuhan, Hubei, China

Should you need more details about datasheet, contact us, pls.

## Revision History

Version No.	Date	Description
1.0	June 24, 2019	Preliminary datasheet

Prurchase service: [prurchase@inphitech.com](mailto:prurchase@inphitech.com)

Support service: [support@inphitech.com](mailto:support@inphitech.com)

Warranty service: [warranty@inphitech.com](mailto:warranty@inphitech.com)